



**Adressierung**

X11.4	.3	.2	.1	.5	Adressenbereich
X12.4	.3	.2	.1	.5	

-	-	-	-	-	0000-07FF
-	-	-	-	x	0800-0FFF
-	-	-	x	-	1000-17FF
-	-	-	x	x	1800-1FFF
-	-	x	-	-	2000-27FF
-	-	x	-	x	2800-2FFF
-	-	x	x	-	3000-37FF
-	-	x	x	x	3800-3FFF
-	x	-	-	-	4000-47FF
-	x	-	-	x	4800-4FFF
-	x	-	x	-	5000-57FF
-	x	-	x	x	5800-5FFF
-	x	x	-	-	6000-67FF
-	x	x	-	x	6800-6FFF
-	x	x	x	-	7000-77FF
-	x	x	x	x	7800-7FFF
x	-	-	-	-	8000-87FF
.	.	.	.	.	.

X15-X17	X16-X17	Kursor	X13.1	.2	Kursor
			X14.1	.2	

-	x	quasigr. Darst.	-	x	blinkend
x	-	intensiv hell	x	-	ruhend

**MDN-Anschluss (Steckbelugung x5)**

A5 - VIDEO, A3 - BSYN, A1 - INTENS, B4 - B2 - Masse